

FERRAZ SHAWMUT DRIVE FUSE SELECTION TABLE

Allen Bradley Powerflex 40 22B Series 100VAC to 240VAC

100-120V AC, 1-Phase Input - 0-230V, 3-Phase Output							
IP/20 NEMA Type Open Catalogue Number	Flange Mount Catalogue Number	Output Ratings		Input Ratings			Main Fuse
		kW (HP)	Amps	Voltage Range	kVA	Amps	
22B-V2P3N104	22B-V2P3F104	0.4 (0.5)	2.3	90-132	1.15	9	HSJ15
22B-V5P0N104	22B-V5P0F104	0.75 (1.0)	5	90-132	2.45	20.3	HSJ35
22B-V6P0N104	22B-V6P0F104	1.1 (1.5)	6	90-132	3	24	HSJ40
200-240V AC, 1-Phase Input - 0-230V, 3-Phase Output							
IP/20 NEMA Type Open Catalogue Number	Flange Mount Catalogue Number	Output Ratings		Input Ratings			Main Fuse
		kW (HP)	Amps	Voltage Range	kVA	Amps	
22B-A2P3N104	-	0.4 (0.5)	2.3	180-264	1.15	6	HSJ10
22B-A5P0N104	-	0.75 (1.0)	5	180-264	2.45	12	HSJ20
22B-A8P0N104	-	1.5 (2.0)	8	180-264	4	18	HSJ30
22B-A012N104	-	2.2 (3.0)	12	180-264	5.5	25	HSJ40
200-240V AC, 3-Phase Input - 0-230V, 3-Phase Output							
IP/20 NEMA Type Open Catalogue Number	Flange Mount Catalogue Number	Output Ratings		Input Ratings			Main Fuse
		kW (HP)	Amps	Voltage Range	kVA	Amps	
22B-B2P3N104	22B-B2P3F104	0.4 (0.5)	2.3	180-264	1.15	2.5	HSJ6
22B-B5P0N104	22B-B5P0F104	0.75 (1.0)	5	180-264	2.45	5.7	HSJ10
22B-B8P0N104	22B-B8P0F104	1.5 (2.0)	8	180-264	4	9.5	HSJ15
22B-B012N104	22B-B012F104	2.2 (3.0)	12	180-264	5.5	15.5	HSJ25
22B-B017N104	22B-B017F104	3.7 (5.0)	17.5	180-264	8.6	21	HSJ30
22B-B024N104	22B-B024F104	5.5(7.5)	24	180-264	11.8	26.1	HSJ40
22B-B033N104	22B-B033F104	7.5(10.0)	33	180-264	16.3	34.6	HSJ60

Ferraz Shawmut HSJ fuses are intended to provide both branch circuit and drive protection. Fuse selection must be in accordance with drive manufacturers recommendations and conform to applicable national and local electrical codes. Recommended fuse ratings were selected for the maximum HP specified for the drive by the manufacturer, based on the most currently available information at the time. Fuses shown will minimize the amount of energy passed by the fuse under short circuit conditions, however, in some cases, component damage may result. Recommended HSJ fuse sizes are for non-bypass mode applications only.

Ferraz Shawmut 374 Merrimac St. Newburyport, MA 01950-1998
Phone: 978-462-6662 Fax: 978-462-0181
Cust. Serv. Fax: 800-535-8114 Tech. Serv. Fax: 800-535-8103
www.ferrazshawmut.com/OEM



March 2006